



COMMERCIAL FIXTURES WA SERIES



FEATURES AND BENEFITS

- Clear acrylic diffuser with prismatic bottom and ribbed linear sides
- Diffuser self-aligns and hinges from either side for easy maintenance
- Available in (L)s from 24 upto 96 inches
 - Two and four lamp configuration
- Single or continuous row mounting capability
 - Surface, stem or chain mountable

ADDITIONAL OPTIONS

- Emergency battery backup
 - Chrome reflector
- Also Available for T5 lamps

APPLICATIONS

Economically designed narrow wraparound luminaire with low brightness linear sides, provide reliable and efficient lighting. Ideal for use in indoor applications, where low glare and ease of installation is required, such as homes, modular homes, mobile homes, stores and public buildings.

9" WRAP AROUND

WA9-2-F17T8-120V • 92353

24" (L) • 9.25" (W) • 3.3" (D) • 120 Volt
Uses Two F17T8 Lamps*

WA9-2-F32T8-120V • 92355

48" (L) • 9.25" (W) • 3.3" (D) • 120 Volt
Uses Two F32T8 Lamps*

11" WRAP AROUND

WA11-2-F17T8-120V • 92406

24" (L) • 11.3" (W) • 3.375" (D) • 120 Volt
Uses Two F17T8 Lamps*

WA11-2-F96T8-120V • 92410

96" (L) • 11.3" (W) • 3.375" (D) • 120 Volt
Uses Two F96T8 Lamps*

WA11-2-F32T8-120V • 92407

48" (L) • 11.3" (W) • 3.375" (D) • 120 Volt
Uses Two F32T8 Lamps*

WA11-2-F96T12-120V • 92404

96" (L) • 11.3" (W) • 3.375" (D) • 120 Volt
Uses Two F96T12 Lamps*

15" WRAP AROUND

WA15-4-F17T8-120V • 92424

24" (L) • 16" (W) • 3.375" (D) • 120 Volt
Uses Four F17T8 Lamps*

WA15-4-F96T8-120V • 92428

96" (L) • 16" (W) • 3.375" (D) • 120 Volt
Uses Four F96T8 Lamps*

WA15-4-F32T8-120V • 92426

48" (L) • 16" (W) • 3.375" (D) • 120 Volt
Uses Four F32T8 Lamps*

WA15-4-F96T12-120V • 92422

96" (L) • 16" (W) • 3.375" (D) • 120 Volt
Uses Four F96T12 Lamps*

WRAP AROUND TANDEM

WA11T-4-F32T8-120 • 92476

96" (L) • 11.3" (W) • 3.375" (D) • 120 Volt
Uses Four F32T8 Lamps*

WA15T-8-F32T8-120V • 92482

96" (L) • 16" (W) • 3.375" (D) • 120 Volt
Uses Eight F32T8 Lamps*